

Setup and use procedure: RFID terminal (Gen.1 -1 card)

This procedure is used to remove all smart cards and resume the initial configuration.

You must have in hand:

- a) The configuration card
- b) Optional, one or more key rings
- c) The terminal is powered on.
 - Open the front panel by unscrewing the four screws.
 - Identify mini switches #1 and #2 (dip switch #1 and #2).
 - For each switch, using a sharp tool, toggle the mini switches from right to left and then from left to right, or vice versa. L'a/ichage indique « ...RESET CARDS... » ou « ...RESET COMPTEURS... ».
 - Put the front panel back in place.
 - Turn off the power supply to the terminal.
 - Put the power back on, you have 60 seconds to present the configuration card.
- You can then follow the instructions for setting up badges.

Usage:

- Start the load:
Present any badges in front of the card reader when the gun is not plugged in or after plugging it in.
When the session is activated, a message reads "Accepted" with the user's card number.
The session ends when you unplug the gun.

NOTE: Using the card marked "CONFIGURATION", you can produce a list of users with their energy consumption in kWh. Also, add one or more



TechnoVE INC.

7804 Maurice-Guillemette Street
G9H 4Y7 Bécancour, Quebec
Site: <https://technove.ca/>
Number: (819) 868 1907
Email: info@technove.ca

users, then remove a user. Finally, you can always activate the terminal or, conversely, activate the access control.

- **Produce the list of users:** Present the configuration card once, then a second time to confirm.

The menu is marked with "LIST USERS?". Present the configuration card to say "YES". The user analysis begins.

(The list of users is created starting with user #0 followed by every 10 seconds by other users. With the user number, the energy consumption is recorded).

- **Add user(s):** Present the configuration card once, then a second time to confirm.

The menu is marked with "LIST USERS?".
Wait 10 seconds for the "ADD USERS?" menu. Present the configuration card to say "YES".

The menu is: "NEW CARD START." Present the badges to be added in turn. At the end, wait 20 seconds to finish.

- **Remove a user:** Present the configuration card once, then a second time to confirm.

The menu is marked with "LIST USERS?".
Wait 10 seconds for the "ADD USERS?" menu. Wait 10 seconds for the "REMOVE USER?" menu. Present the configuration card to say "YES".

The menu has /iche'=> REMOVE CARD# nn'.
If the badge number is deleted, confirm the deletion with the configuration card.

- **Activate the terminal permanently:** Present the configuration card once, then a second time to confirm.

The menu is marked with "LIST USERS?".
Wait 10 seconds for the "ADD USERS?" menu

TechnoVE INC.



7804 Maurice-Guillemette Street
G9H 4Y7 Bécancour, Quebec
Site: <https://technove.ca/>
Number: (819) 868 1907
Email: info@technove.ca

Wait 10 seconds for the "REMOVE USER?" menu.

Wait 10 seconds for the "ACTIVATE PERMANENCE?" menu.

Present the configuration card to say "YES".

The menu reads "**ACTIVATION PERMA**".

It's done.

- **Enable access control: Present the configuration card once, then a second time to confirm.**

The menu is marked with "LIST USERS?".

Wait 10 seconds for the "ADD USERS?" menu. Wait 10 seconds for the "REMOVE USER?" menu. Wait 10 seconds for the menu

"ACTIVATE CNTRL CARD?". Present the configuration card to say "YES".

The menu reads "**CONTROL BY CARD* ".

It's done.



TechnoVE INC.

7804 Maurice-Guillemette Street

G9H 4Y7 Bécancour, Quebec

Site: <https://technove.ca/>

Number: (819) 868 1907

Email: info@technove.ca