

## Setup and use procedure: RFID terminal (LED 3 cards)

### Usage:

- Add bullets:
  - Pass the Cyan card (the LED becomes Cyan blue);
  - Add all badges/chips you want within 60 seconds
  - Wait a few seconds and the menu for adding chips will stop.
- Enable "Always" mode:
  - Pass the Violet card (the LED becomes purple).
  - Give one of the RFID badges.
- Disable "Always" mode:
  - Pass the Violet card (the LED becomes purple).
  - Give one of the RFID badges.
- Remove all terminal chips:
  - Pass the RESET card.

### Configure Programming Cards:

- Start the terminal to enter the master card configuration mode (you will have 1 minute)
- When the LED is solid red, pass the 3 master cards in the following order:
  1. Cyan (adding a bullet point)
  2. Purple (enabling "Always" mode)
  3. Reset (removing chips)
- After playing the 3 cards, the terminal will complete its configuration.



**TechnoVE INC.**  
7804 Maurice-Guillemette Street  
G9H 4Y7 Bécancour, Quebec  
Site: <https://technove.ca/>  
Number: (819) 868 1907  
Email: [info@technove.ca](mailto:info@technove.ca)